

optical modulation based on a modulating signal obtained by adding a redundancy code to a transmission data code;

✓ converting the optical signal transmitted by said optical fiber transmission line into an electrical signal;

✓ detecting a bit error of said electrical signal;

✓ controlling said chirp parameter so that said bit error detected is reduced; and

✓ correcting said bit error of said electrical signal according to said redundancy code, wherein said detecting including counting the number of corrections of said bit error obtained in said correcting. (26-377)

6031.644

2. (AS ONCE AMENDED) A method according to claim 1, wherein said controlling including switching the sign of said chirp parameter

3. (AS ONCE AMENDED) A method according to claim 2, wherein:
said outputting including generating said optical signal by optical modulation using a Mach-Zehnder optical modulator; and
controlling including switching an operating point of said Mach-Zehnder optical modulator.

4. (AS ONCE AMENDED) A method according to claim 1, said outputting including adjusting said chirp parameter to an optimum value so that said bit error detected is minimized.

5. (AS ONCE AMENDED) A method according to claim 4, wherein:
outputting including generating said optical signal by optical modulation using an electroabsorption optical modulator; and
controlling including changing a bias voltage to be applied to said electroabsorption optical modulator.

6. (CANCELLED)

7. (AS ONCE AMENDED) A system comprising:
first and second terminal devices; and

an optical fiber transmission line connecting said first and second terminal devices,
said first terminal device comprising:

an optical transmitter outputting an optical signal having a chirping determined
by a chirp parameter to said optical fiber transmission line, said optical transmitter
generating said optical signal by optical modulation based on a modulating signal
obtained by adding a redundancy code to a transmission data, and

a control unit controlling said chirp parameter according to a control signal, said
control unit correcting said bit error of said electrical signal according to said redundancy
code;

said second terminal device comprising:

an optical receiver converting the optical signal transmitted by said optical fiber
transmission line into an electrical signal,

a monitor unit detecting a bit error of said electrical signal, said monitor unit
comprising counting the number of corrections of said bit error obtained by said control
unit, and

means for transmitting supervisory information on said bit error detected to said
first terminal device; whereby said control signal is generated in said first terminal device
so that said bit error detected is reduced

8. (AS ONCE AMENDED) A system according to claim 7, wherein:
said optical transmitter comprises a light source outputting continuous wave (CW) light,
and a Mach-Zehnder optical modulator for modulating said CW light to generate said optical
signal; and

said control unit includes means for switching an operating point of said Mach-Zehnder
optical modulator, thereby switching the sign of said chirp parameter.

9. (AS ONCE AMENDED) A system according to claim 7, wherein:
said optical transmitter comprises a light source for outputting continuous wave (CW)
light, and an electroabsorption optical modulator for modulating said CW light to generate said
optical signal; and

said control unit includes means for changing a bias voltage to be applied to said
electroabsorption optical modulator, thereby adjusting said chirp parameter to an optimum

value so that said bit error detected is minimized.

10. (AS ONCE AMENDED) A system according to claim 7, wherein:
said optical transmitter comprises a light source outputting continuous wave (CW) light,
an encoder adding the redundancy code to the transmission data code to thereby generate the
modulating signal, an optical modulator modulating said CW light according to said modulating
signal to thereby generate said optical signal;
said optical receiver includes a decoder correcting said bit error of said electrical signal
according to said redundancy code; and
said monitor unit includes means for counting the number of corrections of said bit error
obtained by said decoder.
11. (AS ONCE AMENDED) A system according to claim 7, wherein:
said first terminal device further comprises an optical amplifier amplifying the optical
signal output from said optical transmitter.
12. (AS ONCE AMENDED) A system according to claim 7, wherein:
said second terminal device further comprises an optical amplifier amplifying the optical
signal to be received by said optical receiver.
13. (AS ORIGINAL) A system according to claim 7, wherein said optical fiber
transmission line is provided by a dispersion shifted fiber having a zero-dispersion wavelength
near $1.55\mu\text{m}$.
14. (AS ORIGINAL) A system according to claim 7, wherein said optical fiber
transmission line is provided by a single-mode fiber having a zero-dispersion wavelength near
 $1.3\mu\text{m}$.
15. (AS ONCE AMENDED) A system according to claim 14, wherein said first
terminal device further comprises a dispersion compensating fiber compensating for chromatic
dispersion occurring in said optical fiber transmission line, and an optical amplifier amplifying
the optical signal output from said optical transmitter.